

Setting up Asterisk at Home with ENUM for inbound calls via IAX2

Contributed by Kevan

For an explanation of ENUM and how to use it for outbound calls via Asterisk at Home click [HERE](#)

If you would like to configure your AAH box to support SIP ENUM calls click [here](#).

Setting up Asterisk at Home/Trixbox with ENUM for inbound calls via IAX2

- 1) Connect to the web interface on your AAH/Trixbox (Asterisk at Home) server.
- 2) Click on Asterisk Management Portal and login.
- 3) Click on the Maintenance link and then click the Config Edit link on the left hand side.
- 4) Find and click on the `iax.conf` link on the left hand side of the page.
- 5) Insert the following at the bottom of the file:

```
[guest]
type=user
context=from-pstn
```
- 6) Click the Update button at the bottom of the page.
- 7) Click the Reload Configs link at the top of the page to read in your settings.
- 8) Close the `phpconfig` window and return to the Asterisk@Home window.
- 9) Make sure that you have a DID Route (AAH 1.x) or a Incoming Route (AAH 2.x) for the number you will be receiving calls from via ENUM. The DID should be entered as 12223334444 (make sure you include the leading 1 that is how the calls will be received).
- 10) Don't forget - if your AAH box is behind a firewall, you will need to port forward port 4569/udp to your server.
- 11) Your Asterisk box is ready to accept a SIP protocol ENUM call. If you haven't already created an ENUM record at e164.org, click [here](#) for our step by step e164.org guide.

If you would like to configure your AAH box to also support SIP ENUM calls click [here](#).